

Achieving Type 2 “No Damage” Motor Start Protection

Square D TeSys D Line (Telemecanique) IEC Class 10 Overload Relay & Mersen Fuses

Type 2 “No Damage” Protection - What Is It and Which Fuses Are Best?

Type 2 protection, also referred to as “no damage” protection, simply means that if a short circuit occurs, the short circuit protective device will operate fast enough to prevent fault current damage to healthy equipment in the system. Tests show that current-limiting fuses are the best choice for the protection of the motor controllers if damage-free performance is required. To ensure that correct fuse choices are made, short circuit tests must be made on every possible combination of motor control and fuse. This sheet summarizes a major manufacturer’s motor starter and the Mersen time-delay fuses which give Type 2 “no damage” protection. All combinations are UL witnessed and certified.

200 Volt, Three-Phase Motors

HP	Contactor	OLR	Class J	Class CC	SCCR (kA)
1/2	LC1D09	LRD07	AJT5	ATDR8	100
3/4	LC1D09	LRD08	AJT5	ATDR12	100
1	LC1D09	LRD10	AJT20	ATDR30	100
1 1/2	LC1D09	LRD12	AJT20	ATDR30	100
2	LC1D09	LRD12	AJT20	ATDR30	100
3	LC1D12	LRD16	AJT20	ATDR30	100
10	LC1D40	LRD3355	AJT60	-	100
15	LC1D50	LRD3357	AJT70	-	100
20	LC1D65	LRD3359	AJT100	-	100
25	LC1D80	LRD3363	AJT110	-	100
30	LC1D115	LR9D5569	AJT150	-	100
40	LC1D150	LR9D5569	AJT200	-	100

230 Volt, Three-Phase Motors

HP	Contactor	OLR	Class J	Class CC	SCCR (kA)
1/2	LC1D09	LRD07	AJT5	ATDR8	100
3/4	LC1D09	LRD08	AJT5	ATDR12	100
1	LC1D09	LRD10	AJT20	ATDR30	100
1 1/2	LC1D09	LRD12	AJT20	ATDR30	100
2	LC1D09	LRD12	AJT20	ATDR30	100
3	LC1D12	LRD16	AJT20	ATDR30	100
10	LC1D40	LRD3355	AJT60	-	100
15	LC1D50	LRD3357	AJT70	-	100
20	LC1D65	LRD3359	AJT100	-	100
25	LC1D80	LRD3363	AJT110	-	100
30	LC1D80	LRD3363	AJT110	-	100
40	LC1D115	LR9D5569	AJT150	-	100

460 Volt, Three-Phase Motors

HP	Contactor	OLR	Class J	Class CC	SCCR (kA)
1/2	LC1D09	LRD06	AJT2	ATDR5	100
3/4	LC1D09	LRD06	AJT2	ATDR5	100
1	LC1D09	LRD07	AJT5	ATDR8	100
1 1/2	LC1D09	LRD08	AJT5	ATDR12	100
2	LC1D09	LRD08	AJT5	ATDR12	100
3	LC1D09	LRD10	AJT20	ATDR30	100
5	LC1D09	LRD14	AJT20	ATDR30	100
7 1/2	LC1D12	LRD16	AJT20	ATDR30	100
10	LC1D18	LRD21	AJT25	-	100
15	LC1D25	LRD22	AJT35	-	100
15	LC1D32	LRD22	AJT40	-	100
25	LC1D40	LRD3355	AJT60	-	100
30	LC1D40	LRD3355	AJT60	-	100
30	LC1D40	LRD3357	AJT60	-	100
40	LC1D50	LRD3359	AJT70	-	100
50	LC1D65	LRD3359	AJT100	-	100
60	LC1D80	LRD5363	AJT110	-	100
75	LC1D115	LR9D5569	AJT150	-	100
100	LC1D150	LR9D5569	AJT200	-	100

575 Volt, Three-Phase Motors

HP	Contactor	OLR	Class J	Class CC	SCCR (kA)
1/2	LC1D09	LRD05	AJT1-1/2	ATDR2-8/10	100
3/4	LC1D09	LRD06	AJT2	ATDR5	100
1	LC1D09	LRD07	AJT5	ATDR8	100
1 1/2	LC1D09	LRD07	AJT5	ATDR8	100
2	LC1D09	LRD08	AJT5	ATDR12	100
3	LC1D09	LRD08	AJT5	ATDR12	100
5	LC1D09	LRD12	AJT20	ATDR30	100
7 1/2	LC1D12	LRD16	AJT20	ATDR30	100
10	LC1D18	LRD16	AJT20	ATDR30	100
15	LC1D25	LRD21	AJT25	-	100
20	LC1D32	LRD22	AJT40	-	100
30	LC1D40	LRD3355	AJT60	-	100
40	LC1D50	LRD3357	AJT70	-	100
50	LC1D65	LRD3359	AJT100	-	100
75	LC1D115	LR9D5367	AJT125	-	100
100	LC1D115	LR9D5569	AJT150	-	100
125	LC1D150	LR9D5569	AJT200	-	100

[www.squared.com/.../iec_contactors_starters.nsf/unid/B7D67A0C9FB16F8285256F6900567C4E/\\$file/Shawmutt10.htm](http://www.squared.com/.../iec_contactors_starters.nsf/unid/B7D67A0C9FB16F8285256F6900567C4E/$file/Shawmutt10.htm) - 22k

USA T 978 462 6662 F 978 462 0181 info.nby@mersen.com
CANADA T 416 252 9371 F 416 252 6572 sales.tor@mersen.com

ep-us.mersen.com

FERRAZ SHAWMUT IS NOW MERSEN

MERSEN

Achieving Type 2 “No Damage” Motor Start Protection

Square D TeSys D Line (Telemecanique) IEC Class 10 Overload Relay & Mersen Fuses

200 Volt, Three-Phase Motors

HP	Contactor	OLR	Class J	Class CC	SCCR (kA)
1/2	LC1D09	LRD07	AJT5	ATDR8	100
3/4	LC1D09	LRD08	AJT5	ATDR12	100
1	LC1D09	LRD10	AJT20	ATDR30	100
1 1/2	LC1D09	LRD12	AJT20	ATDR30	100
2	LC1D09	LRD12	AJT20	ATDR30	100
3	LC1D12	LRD16	AJT20	ATDR30	100
10	LC1D40	LRD3355	AJT60	-	100
15	LC1D50	LRD3357	AJT70	-	100
20	LC1D65	LRD3359	AJT100	-	100
25	LC1D80	LRD3363	AJT110	-	100
30	LC1D115	LR9D5569	AJT150	-	100
40	LC1D150	LR9D5569	AJT200	-	100

230 Volt, Three-Phase Motors

HP	Contactor	OLR	Class J	Class CC	SCCR (kA)
1/2	LC1D09	LRD07	AJT5	ATDR8	100
3/4	LC1D09	LRD08	AJT5	ATDR12	100
1	LC1D09	LRD10	AJT20	ATDR30	100
1 1/2	LC1D09	LRD12	AJT20	ATDR30	100
2	LC1D09	LRD12	AJT20	ATDR30	100
3	LC1D12	LRD16	AJT20	ATDR30	100
10	LC1D40	LRD3355	AJT60	-	100
15	LC1D50	LRD3357	AJT70	-	100
20	LC1D65	LRD3359	AJT100	-	100
25	LC1D80	LRD3363	AJT110	-	100
30	LC1D80	LRD3363	AJT110	-	100
40	LC1D115	LR9D5569	AJT150	-	100

460 Volt, Three-Phase Motors

HP	Contactor	OLR	Class J	Class CC	SCCR (kA)
1/2	LC1D09	LRD06	AJT2	ATDR5	100
3/4	LC1D09	LRD06	AJT2	ATDR5	100
1	LC1D09	LRD07	AJT5	ATDR8	100
1 1/2	LC1D09	LRD08	AJT5	ATDR12	100
2	LC1D09	LRD08	AJT5	ATDR12	100
3	LC1D09	LRD10	AJT20	ATDR30	100
5	LC1D09	LRD14	AJT20	ATDR30	100
7 1/2	LC1D12	LRD16	AJT20	ATDR30	100
10	LC1D18	LRD21	AJT25	-	100
15	LC1D25	LRD22	AJT35	-	100
15	LC1D32	LRD22	AJT40	-	100
25	LC1D40	LRD3355	AJT60	-	100
30	LC1D40	LRD3355	AJT60	-	100
30	LC1D40	LRD3357	AJT60	-	100
40	LC1D50	LRD3359	AJT70	-	100
50	LC1D65	LRD3359	AJT100	-	100
60	LC1D80	LRD5363	AJT110	-	100
75	LC1D115	LR9D5569	AJT150	-	100
100	LC1D150	LR9D5569	AJT200	-	100

575 Volt, Three-Phase Motors

HP	Contactor	OLR	Class J	Class CC	SCCR (kA)
1/2	LC1D09	LRD05	AJT1-1/2	ATDR2-8/10	100
3/4	LC1D09	LRD06	AJT2	ATDR5	100
1	LC1D09	LRD07	AJT5	ATDR8	100
1 1/2	LC1D09	LRD07	AJT5	ATDR8	100
2	LC1D09	LRD08	AJT5	ATDR12	100
3	LC1D09	LRD08	AJT5	ATDR12	100
5	LC1D09	LRD12	AJT20	ATDR30	100
7 1/2	LC1D12	LRD16	AJT20	ATDR30	100
10	LC1D18	LRD16	AJT20	ATDR30	100
15	LC1D25	LRD21	AJT25	-	100
20	LC1D32	LRD22	AJT40	-	100
30	LC1D40	LRD3355	AJT60	-	100
40	LC1D50	LRD3357	AJT70	-	100
50	LC1D65	LRD3359	AJT100	-	100
75	LC1D115	LR9D5367	AJT125	-	100
100	LC1D115	LR9D5569	AJT150	-	100
125	LC1D150	LR9D5569	AJT200	-	100

[www.squared.com/.../iec_contactors_starters.nsf/unid/B7D67A0C9FB16F8285256F6900567C4E/\\$file/Shawmutt10.htm](http://www.squared.com/.../iec_contactors_starters.nsf/unid/B7D67A0C9FB16F8285256F6900567C4E/$file/Shawmutt10.htm) - 22k

USA T 978 462 6662 F 978 462 0181 info.nby@mersen.com
 CANADA T 416 252 9371 F 416 252 6572 sales.tor@mersen.com

ep-us.mersen.com

FERRAZ SHAWMUT IS NOW MERSEN



Achieving Type 2 “No Damage” Motor Start Protection

Square D NEMA Motor Starters and Mersen Fuses

Type 2 “No Damage” Protection - What Is It and Which Fuses Are Best?

Type 2 protection, also referred to as “no damage” protection, simply means that if a short circuit occurs, the short circuit protective device will operate fast enough to prevent fault current damage to healthy equipment in the system. Tests show that current-limiting fuses are the best choice for the protection of the motor controllers if damage-free performance is required. To ensure that correct fuse choices are made, short circuit tests must be made on every possible combination of motor control and fuse. This sheet summarizes a major manufacturer’s motor starter and the Mersen time-delay fuses which give Type 2 “no damage” protection. All combinations are UL witnessed and certified.

200 Volt, Three-Phase Motors							230 Volt, Three-Phase Motors						
HP	Starter	Cat. No.	Heater Size	Class RK1	Class J	SCCR (kA)	HP	Starter	Cat. No.	Heater Size	Class RK1	Class J	SCCR (kA)
1 1/2	0	SB02V02S	B10.2	A6D12R	AJT10	100	1 1/2	0	SB02V02S	B8.20	A6D10R	AJT8	100
2	0	SB02V02S	B12.8	A6D15R	AJT12	100	2	0	SB02V02S	B11.5	A6D15R	AJT12	100
3	0	SB02V02S	B19.5	A6D20R	AJT17-1/2	100	3	0	SB02V02S	B15.5	A6D17-1/2R	AJT15	100
5	1	SC03V02S	B32	A6D30R	AJT30	100	5	1	SC03V02S	B28.0	A6D30R	AJT25	100
7 1/2	1	SC03V02S	B50	A6D50R	AJT45	100	7 1/2	1	SC03V02S	B45	A6D40R	AJT40	100
10	2	SD01V02S	B62	A6D60R	AJT60	100	10	2	SD01V02S	B50	A6D50R	AJT50	100
15	3	SE01V02S	CC81.5	A6D90R	AJT80	100	15	3	SE01V02S	CC68.5	A6D70R	AJT70	100
20	3	SE01V02S	CC112	A6D110R	AJT110	100	20	3	SE01V02S	CC94.0	A6D100R	AJT90	100
25	3	SE01V02S	CC180	A6D150R	AJT125	100	25	3	SE01V02S	CC132	A6D125R	AJT110	100
30	4	SF01V02S	CC156	A6D175R	AJT150	100	30	3	SE01V02S	CC196	A6D150R	AJT150	100
40	4	SF01V02S	CC208	A6D200R	AJT200	100	40	4	SF01V02S	CC180	A6D175R	AJT175	100
50	5	SG01V02SY500	B3.70	A6D250R	AJT250	100	50	5	SG01V02SY500	B3.30	A6D225R	AJT225	100
60	5	SG01V02SY500	B4.15	A6D350R	AJT300	100	60	5	SG01V02SY500	B3.70	A6D250R	AJT250	100
75	5	SG01V02SY500	B5.50	A6D400R	AJT400	100	75	5	SG01V02SY500	B4.15	A6D350R	AJT300	100
							100	5	SG01V02SY500	B6.25	A6D400R	AJT400	100

460 Volt, Three-Phase Motors							575 Volt, Three-Phase Motors						
HP	Starter	Cat. No.	Heater Size	Class RK1	Class J	SCCR (kA)	HP	Starter	Cat. No.	Heater Size	Class RK1	Class J	SCCR (kA)
3	0	SB02V02S	B7.70	A6D9R	AJT8	100	3	0	SB02V02S	B6.25	A6D7R	AJT6	100
5	0	SB02V02S	B12.8	A6D15R	AJT12	100	5	0	SB02V02S	B10.2	A6D12R	AJT10	100
7 1/2	1	SC03V02S	B19.5	A6D20R	AJT17-1/2	100	7 1/2	1	SC03V02S	B15.5	A6D17-1/2R	AJT15	100
10	1	SC03V02S	B25	A6D25R	AJT25	100	10	1	SC03V02S	B19.5	A6D20R	AJT17-1/2	100
15	2	SD01V02S	B36	A6D35R	AJT35	100	15	2	SD01V02S	B28.0	A6D30R	AJT25	100
20	2	SD01V02S	B45	A6D50R	AJT45	100	20	2	SD01V02S	B40	A6D40R	AJT40	100
25	2	SD01V02S	B70	A6D60R	AJT60	100	25	2	SD01V02S	B45	A6D50R	AJT45	100
30	3	SE01V02S	CC64.3	A6D70R	AJT70	100	30	3	SE01V02S	CC50.1	A6D60R	AJT50	100
40	3	SE01V02S	CC87.7	A6D90R	AJT90	100	40	3	SE01V02S	CC68.5	A6D70R	AJT70	100
50	3	SE01V02S	CC121	A6D125R	AJT110	100	50	3	SE01V02S	CC87.7	A6D90R	AJT90	100
60	4	SF01V02S	CC121	A6D150R	AJT125	100	60	4	SF01V02S	CC103	A6D110R	AJT110	100
75	4	SF01V02S	CC167	A6D175R	AJT175	100	75	4	SF01V02S	CC121	A6D150R	AJT125	100
100	5	SG01V02SY500	B3.00	A6D225R	AJT225	100	100	4	SF01V02S	CC167	A6D175R	AJT175	100
125	5	SG01V02SY500	B3.70	A6D250R	AJT250	100	125	5	SG01V02SY500	B3.00	A6D225R	AJT225	100
150	5	SG01V02SY500	B4.15	A6D350R	AJT300	100	150	5	SG01V02SY500	B3.70	A6D250R	AJT250	100
200	5	SG01V02SY500	B6.25	A6D400R	AJT400	100	200	5	SG01V02SY500	B4.15	A6D350R	AJT300	100

* These overloads were not tested. Maximum fuse sizes are for the lower value of over-load which was tested.

** Y500 † Sized larger than code max for single motor.

Disclaimer: Regarding information available in this document, Mersen does not warrant or assume any legal liability or responsibility for the accuracy or usefulness of any information disclosed. The content in this guide is for informational purposes only. All information has been gathered from the individual websites of the product manufacturers listed in this document.