# M

# **Transformer Protection**

**Amp-Trap® CL-14 Series** 

#### MEDIUM VOLTAGE FUSES

5.5kV, 8.25kV, AND 15.5kV CLIP-LOCK MOUNTED FUSES



Mersen Amp-Trap fuses for the protection of transformers and distribution lines deliver overload and short circuit protection. These general purpose current-limiting fuses will melt at current that can be as low as 1.7 times the fuse current ratings up to its maximum interrupting rating. These fuses are designed to withstand the transformer magnetizing inrush current. They are single, double or triple barrels 3 inch diameter (size D) and mount in unique cam-locking clips for superior connections as well as easy installation and replacement.

#### FEATURES/BENEFITS:

- UL listed for compatibility with UL listed equipment.
- Clip-lock mounting for reliable high integrity connection into circuit.
- Current-limiting for superior equipment protection.
- Non-venting for silent operation.
- Metal embossed catalog number and manufacturing date for lasting identification.
- Blown-fuse indicator to give positive identification of open fuse.
  - 1 lb tripped force 0.44 inch

#### HIGHLIGHTS:

- E-Rated
- UL listed

#### APPLICATIONS:

 Protection for 5.5kV to 15.5kV transformers or distribution systems.

### **Ratings:**

#### **Amp-Trap CL-14 Series**

(Indoor or outdoors in a weatherproof enclosure)

#### A055C

Volts: 5.5kV ACAmps: 10 to 600EIR: 63kA Sym

#### A083C:

Volts: 8.25kV ACAmps: 60 to 200E

• **IR:** 70kA Sym

#### A155C

Volts: 15.5kV ACAmps: 10 to 300EIR: 50kA Sym

#### APPROVALS:

 Some UL Listed to standard File E143362



See Fuse Blocks and Holders section for CL-14 Clip-Lock Clips




## 8.25kV CLIP-LOCK MOUNTED FUSES:

#### 8.25kV E-Rated Amp-Trap CL-14 Series

15.70" (399mm) and 15.39 (391mm) Clip Centers (dimension E). Suitable for use indoors or in an enclosure only.

Catalog No.	Amp Rating	No. of Barrels	Indicating	Max Voltage	Max IR RMS Sym	Figure	Dimensions Inches (mm)			
						Figure	A	В	C	E
A083C1D0R0-60E	60E	1	Yes	8.25kV	70kA	A	16.95 (431)	16.26 (413)	0.44 (11.1) Tripped Force 1 lbs.	15.39 (391)
A083C2D0R0-200E	200E	2	Yes	8.25kV	70kA	В	16.95 (431)	16.26 (413)	0.44 (11.1) Tripped Force 1 lbs.	15.39 (391)






Figure A

Figure B